

## 2.0 cu. ft. NeoChef™ Countertop Microwave Oven



- 2.0 cu. ft. Oven Capacity
- Smart Inverter
- EasyClean® Interior
- SmoothTouch™ Glass Controls
- 1,200 Watts
- Sensor Cooking
- 10 Power Levels
- Popcorn Key
- Hexagonal Stable Ring
- LED Interior Light
- Optional Built-in Trim Kit



Shown with optional built-in trim kit

### COLOR AVAILABILITY

- LMC2075ST – Stainless Steel
- LMC2075BD – Black Stainless Steel

### COOKING FEATURES

Oven Capacity	2.0 cu. ft.
Microwave Power Output	1,200 W
EasyClean® Interior	Yes
Sensor Cook Options	7 (Potato, Fresh Vegetable, Frozen Vegetable, Frozen Entrée, Bacon, Rice, Soften Butter)
Power Levels	10
Defrost	4 Options (Meat, Poultry, Fish, Bread)
Sensor Reheat	5 Options (Beverage, Casserole, Pizza, Dinner Plate, Pie)
Popcorn Key	Yes
Custom Settings	No

### CONVENIENCE FEATURES

Control Type	SmoothTouch™ Glass
Turntable Diameter	16"
Metal Rack	No
Clock	Yes
Kitchen Timer	Yes
Completion Beeper	Yes
Turntable On/Off	No
Add 30 Seconds	Yes
Energy Savings Key (Turns Off LED Display)	Yes
Interior Lighting	LED
Child Lock	Yes

### SMART FEATURES

Wi-Fi Enabled	No
ThinQ®	No
SmartDiagnosis™	No

### APPEARANCE / MATERIALS / FINISHES

WideView™ Window	Yes
Interior Color	Gray
Clock Display Color	White LED

### TECHNICAL SPECS

Required Power Supply	120V, 60 Hz
Minimum Circuit Rating	15 Amp
Plug Type	3-Prong
ADA Compliant	Yes

### INCLUDED ACCESSORIES

Glass Turntable

### OPTIONAL ACCESSORIES

30-inch Trim Kit	MK2030NST - Stainless Steel MK2030NBD - Black Stainless Steel
------------------	--

### DIMENSIONS / CLEARANCES / WEIGHT

Product Dimensions (W x H x D)	23 7/8" x 13 9/16" x 19 3/8"
Oven Interior Dimensions (W x H x D)	16 11/16" x 11 1/4" x 18 1/16"
Dimensions with Optional Trim Kit (W x H)	29 23/32" x 19 1/16"
Cut-out Dimensions with Optional Trim Kit (W x D)	25 1/2" X 16 3/4" X 19 1/2"
Carton Dimensions (W x H x D)	27 3/4" x 15 2/5" x 21 1/4"
Approx. Weight (Product / Carton)	33 lbs. / 44 lbs.

### LIMITED WARRANTY

Parts and Labor	1 Year (Carry-in Service)
Magnetron	10 Years (Carry-in Service)